Addressing modes are the ways through which operands are specified.

The address field in a typical instruction formats are relatively small.



## Instruction Format

This address field is used to reference the operand in the memory.

## Different addressing modes are:

- 1. Immediate addressing mode
- 2. Direct addressing mode
- 3. Indirect addresing mode
- 4. Register direct addressing mode
- 5. Register indirect addressing mode
- 6. Displacement addressing mode
- 1. Immediate addressing mode:

In immediate addressing mode the operand value is present in the instruction.

Operand = A

Advantage of immediate addressing mode: No memory reference other than the instruction fetch is required to obtain the operand.

Disadvantage of immediate addressing mode: Size of the number is restricted to the size of

the address field.



# Immediate addressing mode

2. Direct addressing mode:

In direct addressing mode the address field contains the effective address of the operand.

 $\mathsf{E}\mathsf{A} = \mathsf{A}$ 

Advantage of direct addressing mode:

It requires only one memory reference and no special calculation.

Disadvantages od direct addressing mode: It provides only a limited address space.



3. Indirect addressing mode:

In indirect addressing mode the address field refer to the address of a word in memory, which contains a full-length address of the operand.

#### EA = (A)

Here, the parentheses are to be interpreted as meaning contents of.

Advantage of indirect addressing mode: Address range is not limited by address field.

Disadvantage of indirect memory address: Instruction execution requires two memory references to fetch the operand: one to get its address and a second to get its value.



4. Register direct addressing mode:

Register direct addressing mode is similar to direct addressing mode. The only difference is that the address field refers to a register rather than a main memory address.

#### EA = R

Advantages of register direct addressing mode: Only a small address field is needed in the instruction, and no time consuming memory references are required.

Disadvantag f register direct addressing mode: Address space is very limited.



5. Register indirect addressing mode:

Register indirect addressing mode is similar to indirect addressing mode. The only difference is that the address field refers to a register than a main memory. EA = (R)

The advantages and disadvantages of register indirect addressing mode are basically the same as for indirect addressing mode.



<sup>6.</sup> Displacement addressing mode:

Displacement addressing mode combines the capabilities of direct addressing mode and register indirect addressing mode.

EA = A + (R)



## Displacement addressing mode

Difference betwenn Register Direct Addressing Mode and Register Indirect Addressing Mode:

Register Direct Addressing Mode		Register Indirect Addressing Mode
1.	Operand is placed in register.	Operand is placed in Main memory.
2.	Registers are used to store operands.	Registers are used to store address of operand in main memory.
3. oper	Address field contains effective address of and.	Address field contains reference to the effective address of operand.
4.	One register reference for operand.	Two register reference for operand.
5.	Fast	Slow

6.	Easier to access data	Complex
7. oper	Limitation of address field to store and address.	There is no such limit.

Difference betwenn Direct Addressing Mode and Indirect Addressing Mode:

Direct Addressing Mode	Indirect Addressing Mode
1. Address field contains effective address of operand.	Address field contains memory location where effective address is present
2. One memory reference to access operand	Two memory reference to access operand
3. Fast	Slow
4. Address size of operand is limited to size of address field.	No such limitation. Because operand address is stored in main memory.
5. Less calculation to access operand	More calculation to access operand.

Difference betwenn Immediate Addressing Mode and Direct Addressing Mode:

Immediate Addressing Mode		Direct Addressing Mode
1.	Address field contains operand	Address field contains effective address of operand
2.	Operand is in address field	Operand is present in main memory
3.	No memory reference	One memory reference
4.	Fast	Slow

5. Operand size depends on size of address field	No limitation on operand size
--	-------------------------------

Difference between Immediate Addressing Mode and Indirect Addressing Mode:

Immediate Addressing Mode		Indirect Addressing Mode
1.	Address field contains operand	Address field contains memory reference of operand
2.	There is no memory reference	There is two memory reference
3. field	Operand size depends on size of address in instruction	There is no such limit on operand size
4.	Fast	Slow
5.	Operand present in address field	Operand is present in main memory

Q1. There is more than one addressing mode, than how processor determine which addressing mode to use?

Ans. By using mode field. One or more bits in the instruction format can be used as a mode field. The value of the mode field determines which addressing mode is to be used.

Q2. What is effective address ?

Ans. In a system without virtual memory, the effective address will be either a main memory address or a register. In a virtual memory system, the effective address is a virtual address or a register.

### **Related Posts:**

- 1. Structure of Desktop computers
- 2. Logic Gates
- 3. Register Organization
- 4. Bus structure in Computer Organization
- 5. Register Transfer Language
- 6. Numerical problem on Direct mapping
- 7. Registers in Assembly Language Programming
- 8. Array in Assembly Language Programming
- 9. Net 31
- 10. How to start with GNU Simulator 8085
- 11. Cache Updating Scheme
- 12. Cache Memory
- 13. Principle of Cache Memory
- 14. Cache Mapping
- 15. Addition and subtraction in fixed point numbers
- 16. PCI Bus
- 17. Booths Algorithm
- 18. Write a short note on design of arithmetic unit ?
- 19. Write a short note on Array processors ?
- 20. Write a short note on LRU algorithm ?
- 21. What is the format of Micro Instruction in Computer Architecture explain ?
- 22. What is the layout of pipelined instruction in Computer Architecture ?
- 23. Explain the following interfaces in Detail:PCI Bus, SCSI Bus, USB Bus
- 24. What is Memory Organization ? Discuss different types of Memory Organization in Computer System.
- 25. Computer Organization Q and A

- 26. Write short note on improving cache performance methods in detail ?
- 27. What is Multiprocessor ? Explain inter process communication in detail ?
- 28. Briefly explain the concept of pipelining in detail ?
- 29. Discuss the following in detail: RISC architecture, Vector processing ?
- 30. Define the instruction format ? Explain I/O System in detail ?
- 31. Explain the design of arithmetic and logic unit by taking on example ?
- 32. Explain how addition and subtraction are performed in fixed point number ?
- 33. Explain different modes of data transfer between the central computer and I/O device?
- 34. Differentiate between Serial and parallel data transfer ?
- 35. Explain signed magnitude, signed I's complement and signed 2's complement representation of numbers. Find the range of numbers in all three representations for 8 bit register.
- 36. If cache access time is IOOns, main memory access time is 1000 ns and the hit ratio is 0.9. Find the average access time and also define hit ratio.
- 37. Explain hardwired microprogrammed control unit ? What is address sequencer circuit ?
- 38. Explain how a stack organized computer executes instructions? What is Stack?
- 39. Draw and explain the memory hierarchy in a digital computer. What are advantages of cache memory over main memory?
- 40. What is Associative memory? Explain the concept of address space and memory space in Virtual memory.
- 41. What is Paging? Explain how paging can be implemented in CPU to access virtual memory.
- 42. Explain SIMD array processor along with its architectural diagram ?
- 43. Write short notes on
- 44. Draw the functional and structural views of a computer system and explain in detail ?
- 45. Explain general register organization.

- 46. Compare and contrast DMA and I/O processors ?
- 47. Define the following: a) Flynn's taxonomy b) Replacement algorithm
- 48. Explain the various pipeline vector processing methods?
- 49. Describe the language features for parallelism ?
- 50. What are different addressing modes? Explain them.
- 51. Explain any page replacement algorithm with the help of example ?
- 52. What is mapping? Name all the types of cache mapping and explain anyone in detail.
- 53. Explain arithmetic pipeline ?
- 54. Write short notes on, a) SIMD, b) Matrix multiplication c) Instruction format
- 55. Differentiate: a) Maskable and non-maskable interrupt b) RISC and CISC
- 56. Computer Organization Previous Years Solved Questions
- 57. Booths algorithm to muliyiply +5 and -15